



CLVR03XTZ

Alarm and extinguishing control panel



Conventional fire alarm and fire extinguishing control panel with 3 detection zones.

The CLVR03XTZ extinguishing control panel is designed to control an independent zone of the extinguishing system. It has 3 detection zones to act on the extinguishing systems. The zones can be configured independently or combined with each other to activate the extinguishing system.

The CLVR03XTZ control panel provides a log of all the events (history events) that happen in the control panel, as alarms, faults, etc. This log can be downloaded to a computer using the specific management software Loop Explorer 2.

The control panel has 6 programmable outputs that can be used to control remote devices or signalling systems.

The control panel can be configured to provide 2 extinguishing outputs, which can work together, or be divided into principal and reserve.

It has an LCD screen to complement the LED signalling, as well as an additional visual aid. This display can change colour depending on the status of the control unit.

The CLVR03XTZ control panel is fully programmable from the front panel and can be password restricted.

Features:

- Single area extinguishing panel.
- Dual extinguishing output (main and standby).
- Logging of up to 1000 events.
- Dynamic LCD display.
- 4 user access codes.
- 6 programmable relay outputs.
- Approved and certified according to EN12094-1, EN54-2 and -EN54-2.

TECHNICAL FEATURES

Supply voltage	230 Vac	Battery voltage	27,6 Vdc
Supply fuse	2 A	Dimensions	368x324x100mm
Battery	2x12 V	Weight	6 kg
Alarm current	0,235 A	IP protection	IP30
Batteries current	2 A	Standard	EN 12094-1 EN54-2 & EN54-4
Max. ripple current	<200 milivolts		
Sounder output	21 - 28 Vdc		